Phonak Spice+ reference guide

PHONAK life is on

Technical Information

	Models	Battery	External xReceiver	Ear Simulator Max. Gain	Ear Simulator Max. MPO	2 cc Max. Gain	2 cc Max. MPO	Acoustic Coupling: Hook	Mini hook	SlimTube HE	Power SlimTube	SlimTip/SlimTip soft	Open/closed/power dome	cShell	cShell soft	xShell	Telecoil	Categories of Hearing Impairment: Mild hearing loss	Moderate hearing loss	Severe hearing loss	Profound hearing loss
Phonak Ambra, Phonak Solana, Phonak Cassia	Petite	10		51	120	45	118	■	■	■		■	■				■	■	■		
	microM	312		59	128	54	126	■	■	■		■	■				■	■	■	■	
	M H2O	13		59	128	55	126	■	■	■		■	■				■	■	■	■	
	microP	13		64°	131°	60°	129°	■	■	■		■	■				■	■	■	■	
	SP	13		75°	135°	70°	133°	■	■	■		■	■				■		■	■	■
	nano	10																■	■		
	10 Petite	10																■	■	■	
	312 Petite*	312		M 50	M 120	M 40	M 112											■	■	■	
	312 UZ Petite	312		P 60	P 123	P 50	P 117											■	■	■	
	312	312		SP 70	SP 128	SP 60	SP 122											■	■	■	
	312 UZ*	312		UP 79	UP 135	UP 70	UP 130											■	■	■	
	13 UZ*	13																■	■	■	
Audéo S YES	CRT	312	Standard xReceiver (xS)	56	121	44	112					■	■	■	■			■	■		
	CRT	312	Power xReceiver (xP)	62	132	52	125						■	■	■	■		■	■		
	CRT	312	SuperPower xReceiver (xSP)	66	133	58	129							■					■		
Audéo S SMART	CRT	312	Standard xReceiver (xS)	56	121	45	112					■	■	■	■			■	■		
	CRT	312	Power xReceiver (xP)	65	132	55	126						■	■	■	■		■	■		
	CRT	312	SuperPower xReceiver (xSP)	69	133	61	129							■					■		
Audéo S MINI	CRT	10	Standard xReceiver (xS)	56	121	45	112					■	■	■	■			■	■		
	CRT	10	Power xReceiver (xP)	65	132	55	126						■	■	■	■		■	■		
	CRT	10	SuperPower xReceiver (xSP)	69	133	61	129							■					■		
Naída S	UP	675		85°	144°	82°	142°	■	■		■						■		■	■	■
	SP	13		80°	141°	75°	140°	■	■		■						■		■	■	■
	CRT	13	SuperPower plus (xSP plus) **	72	137	65	133							■			■		■	■	■
Nios S H2O	V	13		67°	134°	63°	131°	■	■	■		■	■				■	■	■	■	■
	III	13		67°	134°	63°	131°	■	■	■		■	■				■	■	■	■	■

Phonak AccessLine

	Models	Accessories: Phonak ComPilot /TVLink S	Phonak PilotOne	myPilot	iCom / TVLink	Click'nTalk	iCube	FM Receiver: MyLink+	MLxS or MLxi	ML10i / AS10	ML11i / AS11	ML13i / AS13	ML15i / AS15	FM Transmitter: inspiro	SmartLink+	ZoomLink+	EasyLink+
Phonak Ambra, Phonak Solana, Phonak Cassia	Petite		■														
	microM	■	■	■	■	■	■		▲					▲	▲	▲	▲
	M H2O	■	■	■	■	■	■	■	■				■	■	■	■	■
	microP	■	■	■	■	■	■	■	■			■		■	■	■	■
	SP	■	■	■	■	■	■	■	■			■		■	■	■	■
	nano																
	10 Petite		●					■						■	■	■	■
	312 Petite*		●					■						■	■	■	■
	312 UZ Petite		●					■						■	■	■	■
	312	■	■	■	■	■	■	■	▲					■	■	■	■
	312 UZ*	■	■	■	■	■	■	■	▲					■	■	■	■
	13 UZ*	■	■	■	■	■	■	■	▲					■	■	■	■
Audéo S YES	CRT	■	■	■	■	■	■		▲					▲	▲	▲	▲
	CRT	■	■	■	■	■	■		▲					▲	▲	▲	▲
	CRT	■	■	■	■	■	■		▲					▲	▲	▲	▲
Audéo S SMART	CRT	✦	✦	✦	✦	✦	✦		▲▲					▲▲	▲▲	▲▲	▲▲
	CRT	✦	✦	✦	✦	✦	✦		▲▲					▲▲	▲▲	▲▲	▲▲
	CRT	✦	✦	✦	✦	✦	✦		▲▲					▲▲	▲▲	▲▲	▲▲
Audéo S MINI	CRT																
	CRT																
	CRT																
Naída S	UP	■	■	■	■	■	■	■	■					■	■	■	■
	SP	■	■	■	■	■	■	■	■					■	■	■	■
	CRT	■	■	■	■	■	■	■	■				■	■	■	■	■
Nios S H2O	V	■	■	■	■	■	■	■	■					■	■	■	■
	III	■	■	■	■	■	■	■	■					■	■	■	■

Features

	Models	Binaural Directionality: StereoZoom	auto ZoomControl	ZoomControl	DuoPhone	UltraZoom Premium	UltraZoom Advanced	UltraZoom Standard	UltraZoom Basic	QuickSync	Adaptive Intelligence: FlexControl	FlexVolume	SoundFlow Premium 4 programs	SoundFlow Advanced 3 programs	SoundFlow Standard 2 programs	User Preference Learning	A Phonak has it all: SoundRecover	Real Ear Sound	WhistleBlock	NoiseBlock Premium	NoiseBlock Advanced	NoiseBlock Standard	NoiseBlock Basic	WindBlock	EchoBlock	SoundRelax	WaterResistant	Acoustically Optimized Vent (AOV)*	Channels	Compatibility CROS/BiCROS
microM, M H2O, microP, SP	Phonak Ambra	■	■	■	■	■				■	■	■	■			■	■	■	■	■			■	■	■	■	■	20	■
	Phonak Solana			■			■			■		■		■		■	■	■			■		■			■	■	16	■
	Phonak Cassia							■		■					■	■	■		■			■				■	■	6	■
Petite	Phonak Ambra					■					■	■	■			■	■	■	■	■			■	■	■		■	20	
	Phonak Solana						■					■		■		■	■	■			■		■				■	16	
	Phonak Cassia							■							■	■	■		■			■					■	6	
nano	Phonak Ambra												■			■	■	■	■				■	■	■		■	20	
	Phonak Solana													■		■	■	■		■			■				■	16	
10, 312, 312 UZ Petite	Phonak Ambra				)						■	■	■			■	■	■					■	■	■		■	20	
	Phonak Solana					)						■		■		■	■			■			■				■	16	
	Phonak Cassia						)								■	■	■					■					■	6	
312, 312 UZ, 13 UZ	Phonak Ambra	■	■	■	■	)				■	■	■	■			■	■	■					■	■	■		■	20	■
	Phonak Solana			■			)			■		■		■		■	■			■			■				■	16	■
	Phonak Cassia							)		■					■	■	■					■					■	6	■
Audéo S YES / SMART	IX	■	■	■	■	■				✺	■	■	■			■	■	■	■	■			■	■	■		■	20	■
	V			■			■			✺		■		■		■	■	■			■		■				■	16	■
	III							■		✺					■	■	■		■			■					■	6	■
	Audéo S SMART I								■							■	■				■							4	
Audéo S MINI	IX					■							■			■	■	■	■	■			■	■	■		■	20	
	V						■							■		■	■	■			■		■				■	16	
	III							■							■	■	■		■			■					■	6	
Naída S	SP + UP + CRT IX	■	■	■	■	■				■	■	■	■			■	■	■	■	■			■	■	■	■	■	20	■
	SP + UP + CRT V			■			■			■		■		■		■	■	■			■		■			■	■	16	■
	SP + UP + CRT III							■		■					■	■	■		■			■				■	■	6	■
Nios S H2O	V			■			■			■		■		■		■	■	■			■		■			■	■	16	■
	III							■		■					■	■	■		■			■				■	■	6	■

** Also compatible with Standard and Power xReceivers

* Also available as UP model

° Measured with tone hook

▲ Requires iCom

● Requires remote control option

■ Requires telecoil option

✦ Not compatible with Audéo S SMART I

Only available for M H2O

) Only available for 312 UZ Petite, 312 UZ, 13 UZ

✺ Only available for Audéo S SMART

* Available for cShell/cShell soft, xShell, SlimTip/SlimTip soft and custom products