

Phonak

Charger BTE RIC

Technical Data

Dimensions (L x W x H)	95 x 61 x 73 mm (3.7 x 2.4 x 2.9 ")	
Weight	103 g (3.6 oz)	
Color	Champagne	
Operating conditions	5° to +40° Celsius (41° to 104°Fahrenheit)	
Transport and storage conditions	-20° to +60° Celsius (-4° to +140° Fahrenheit)	
Humidity during transportation	Up to 90% (non condensing)	
Humidity during storage	0% to 70% (non condensing)	
Humidity during operation	0% to 85% (non condensing)	
Atmospheric pressure during use	800 hPa to 1060 hPa	
Included Parts	Power supply USB-C Cable	
External Interfaces	USB-C port	
Battery	None	
Charging time*	0% to 100%	3h
	0% to 80%	1.5h
	30 min. fitting	10 min.

* Actual charging time depends on the remaining battery life, but it will not exceed 3 hours.



Power supply

Input	Type: DC, stabilized 5 V +/- 5% Max. current: 500 mA
-------	---

Important notices

The battery cannot be over-charged. It may become warm during charging. Use only original Phonak chargers with your Phonak hearing aids.



Sonova AG · Laubisrütistrasse 28
CH-8712 Stäfa · Switzerland

A Sonova brand

PHONAK
life is on