



Phonak Ambra 312 Petite (M)


Compact ITE, battery size 312 (for fitting range, product details and available options, please see Product Information or visit www.phonakpro.com).

Petite devices do not have wireless functionality. Unless otherwise specified, all data obtained are measured with 5 mm tubing and Phonak Target measurement settings.


Ear simulator data

EN / IEC 60118 and IEC 60711

Output sound pressure level




Acoustic gain



Frequency range	<100 Hz - 8200 Hz		
Total harmonic distortion	500 Hz	800 Hz	1600 Hz
	2.5%	2.5%	2%
Battery current	Quiescent	Working	
	1.1 mA	1.2 mA	
Equivalent input noise level	19 dB SPL		

Induction coil sensitivity



Dynamic data


Compression	Attack time	Recovery time
	10 ms	50 ms

Note: Using pure tone measurements with a digital hearing instrument can result in a wavy frequency response. This is an artifact resulting from the use of a narrowband input signal and does not effect the actual performance with naturally occurring broadband input signals.


2cm³ coupler data

ANSI S3.22-2003

Output sound pressure level




Acoustic gain



Frequency range	<100 Hz - 7900 Hz		
Total harmonic distortion	500 Hz	800 Hz	1600 Hz
	1.5%	1.5%	1%
Equivalent input noise level	19 dB SPL		


Induction coil sensitivity



Dynamic data

Compression	Attack time	Recovery time
	10 ms	50 ms

Input / Output characteristics at 2000 Hz




Technical Data

Phonak Ambra 312 Petite (P)


Ear simulator data

EN / IEC 60118 and IEC 60711

Output sound pressure level




Acoustic gain



Frequency range	<100 Hz - 7500 Hz		
Total harmonic distortion	500 Hz	800 Hz	1600 Hz
	2.5%	2.5%	2%
Battery current	Quiescent	Working	
	1.1 mA	1.2 mA	

Equivalent input noise level 19 dB SPL

Induction coil sensitivity




Dynamic data

Compression	Attack time	Recovery time
	10 ms	50 ms


2cm³ coupler data

ANSI S3.22-2003

Output sound pressure level




Acoustic gain



Frequency range	<100 Hz - 7200 Hz		
Total harmonic distortion	500 Hz	800 Hz	1600 Hz
	1.5%	1.5%	1.5%

Equivalent input noise level 19 dB SPL


Induction coil sensitivity



Dynamic data

Compression	Attack time	Recovery time
	10 ms	50 ms

Input / Output characteristics at 2000 Hz



PHONAK

Technical Data


Phonak Ambra 312 Petite (SP)

(available in specific countries only)


Ear simulator data

EN / IEC 60118 and IEC 60711

Output sound pressure level




Acoustic gain



Frequency range	< 100 Hz - 7500 Hz		
Total harmonic distortion	500 Hz	800 Hz	1600 Hz
	1.5%	1.5%	1%
Battery current	Quiescent	Working	
	1.1 mA	1.2 mA	

Equivalent input noise level 19 dB SPL

Induction coil sensitivity




Dynamic data

Compression	Attack time	Recovery time
	10 ms	50 ms


2cm³ coupler data

ANSI S3.22-2003

Output sound pressure level




Acoustic gain



Frequency range	< 100 Hz - 7200 Hz		
Total harmonic distortion	500 Hz	800 Hz	1600 Hz
	1%	1%	1%

Equivalent input noise level 19 dB SPL


Induction coil sensitivity



Dynamic data

Compression	Attack time	Recovery time
	10 ms	50 ms

Input / Output characteristics at 2000 Hz



PHONAK